



Rogue Audio Inc.

PO Box 1076 Brodheadsville, PA 18322

tel: (570) 992-9901

fax: (570) 992-1978

Triton Phono Preamplifier Settings

Capacitance Dip-1, Dip-2

Switch position	Left Channel	Right Channel
No switch on	0 pF	0 pF
A	47 pF	47 pF
B	150 pF	150 pF
C	470 pF	470 pF
D	1,000 pF	1,000 pF

Resistance loading Dip-3, Dip-4, Dip-5, Dip- 6

	Left Channel	Right Channel
A	20 Ohms	20 Ohms
B	50 Ohms	50 Ohms
C	100 Ohms	100 Ohms
D	300 Ohms	300 Ohms
E	1 K Ohms	1 K Ohms
F	47 K Ohm	47 K Ohms
G	75 K Ohms	75 K Ohms
H	100 K Ohms	100 K Ohms

Gain in dB Dip-7, Dip-8

Switch position	Left Channel	Right Channel
A	45 dB	45 dB
B	55 dB	55 dB
C	60 dB	60 dB
D	65 dB	65 dB